

# PRO LINK CONNECTOR

## WIDEX PRO LINK™ CONNECTOR



### MAIN FEATURES

PRO LINK enables you to reliably fit all WidexLink hearing aids wirelessly with COMPASS GPS software

- With PRO LINK Connector, you can also easily fit the CIC-Micro hearing aids
- Standard replaceable battery
- One solution, easy set-up, easy fitting

PRO LINK Connector device is for professional use only

### TECHNICAL SPECIFICATIONS

#### COMPONENTS

PRO LINK Connector  
Integrated neck loop with easy open/close snap  
Battery compartment for type LR44 battery  
Test button for checking battery is charged  
Retail box, which can be used for storing in between use

#### CONNECTIONS

2 jack plugs to fit into jack ports on PRO LINK

#### OPERATING CONDITIONS

Operating humidity:	Relative humidity < 90%
Operating temperature:	+5°C to +40°C
Storage temperature:	-10°C to +50°C
Compatibility	Non-wireless hearing aids from Widex, type CIC-M COMPASS GPS 3*
Expected service life	5 years

\* For standard Widex-Link hearing aids, use PRO LINK without the PRO LINK Connector.

# PRO LINK CONNECTOR

---

## PHYSICAL PROPERTIES

Dimensions:	26/43/16 mm (l/w/h)
Weight:	25 g.
Color:	Anthracite Grey

## OVERVIEW

1. Battery compartment
2. Neck loop with open/close snap
3. Jack connectors
4. Connector for CIC-Micro cables
5. Push button
6. Battery LED

