

WIDEX MAGNIFY™ MINI RIC RECHARGEABLE WITH V.2 RIC P-RECEIVER



The WIDEX mRIC R D is part of the WIDEX MAGNIFY™ family. Built around the WIDEX MAGNIFY™ platform to deliver better sound via TruAcoustics™ and all on a brand-new chip with greater connectivity.


Fitting mRIC is easier than ever before, thanks to TruAcoustics™ giving a more powerful personalised sound.

The mRIC is powered by a built-in lithium-ion battery and charged wirelessly by a matching table charger.

WIDEX is offering a brand new design and hearing aid form factor in one-tone colours. App support is offered via the direct bluetooth connection to iOS, which also enables connection to TV PLAY.

- Direct mobile wireless connectivity (2.4 GHz)
- Compatible with the DEX assistive listening devices
- 4 performance levels: 440/330/220/110
- Uses V.2 Easyware P-receiver
- Works with a physically smaller and more powerful receiver that covers a larger fitting range
- Powered by a lithium-ion rechargeable battery
- Hearing loss up to severe-to-profound
- Protection class IP68

SUGGESTED FITTING RANGE



STANDARD TECHNOLOGY

- WIDEX MAGNIFY™ platform with Personal Gain Integrator
- TruAcoustics™ for improved sound and fitting

KEY FEATURES	440	330	220	110
Performance	*****	*****	****	**
Processing and fine-tuning channels	15	12	10	6
TruAcoustics™ with Personal Gain Integrator	•	•	•	•

CONNECTIVITY

2.4 GHz control (Android and iOS)	•	•	•	•
2.4 GHz audio streaming (iOS)*	•	•	•	•
WidexLink to DEX assistive listening devices**	•	•	•	•

APPS FOR iOS AND ANDROID

MAGNIFY App with SoundSense Learn	•	•	•	•
MAGNIFY App	•	•	•	•
TONELINK App	•	•	•	•
COM-DEX App	•	•	•	•


FEATURES

Adaptation manager	•	•	•	•
Fluid Sound Analyser (sound classes)	11 (IE)	7 (IE)	4	3
Programs	5	4	3	3
Smartwind Manager	•			
High-frequency boost	•			
Speech Enhancer RT	RT/IE	IE		
Digital Pinna	•	•		
HD Locator	•	•	•	
TruSound Softener	•	•	•	
SoundSense Adapt	•	•	•	
Preference Control	•	•	•	•
Programmable Push Button***	•	•	•	•
Soft-level noise reduction	•	•	•	•
Noise Reduction	•	•	•	•
ZEN IE	•	•	•	•
Audibility Extender	•	•	•	•


*Ready for direct Android streaming. **Also includes DEX assistive listening devices: TV-DEX, COM-DEX, RC-DEX, FM+ DEX, TV-PLAY. ***Programmable: As a program button and an on/off switch, As a sound adjustment button and an on/off switch, As a dedicated on/off switch.

For information regarding which devices WIDEX MAGNIFY, direct streaming, is compatible with, please go to: global.widex.com/compatibility


MAXIMUM OUTPUT - EAR SIMULATOR




MAXIMUM OUTPUT - 2CC COUPLER



OUTPUT - EAR SIMULATOR



OUTPUT - 2CC COUPLER



Technical data:

Typical data obtained through standard pure tone measurements. Hearing aid set to Compass Reference Test Gain, unless stated otherwise. Measured using a standard ITE coupler without wax guard. For further information, please contact Widex at global.widex.com.

		EAR SIMULATOR IEC 60118-0:1983 + A1:1994	2CC COUPLER IEC 60118-0:2015, ANSI S3.22-2014
OSPL90	1600 Hz	131 dB SPL	122 dB SPL
	Peak	133 dB SPL	123 dB SPL
	Average	127 dB SPL	121 dB SPL
Acoustic output (Input 60 dB SPL)	1600 Hz	116 dB SPL	107 dB SPL
	Peak	119 dB SPL	109 dB SPL
	Average	108 dB SPL	104 dB SPL
Full-on gain (Input 50 dB SPL, Compass Full-on gain)	1600 Hz	68 dB	59 dB
	Peak	71 dB	65 dB
	Average	69 dB	60 dB
Acoustic frequency range		100 Hz - 8050 Hz	100 Hz - 7550 Hz
Harmonic distortion (typical)	500 Hz	<2%	<2%
	800 Hz	<2%	<2%
	1600 Hz	<2%	<2%
Equivalent input noise		17 dB SPL	20 dB SPL
Battery drain (standby)		1.27 mA	1.27 mA
Battery drain*		1.43 mA	1.45 mA
Battery life* (Rechargeable lithium-ion battery)		35 h	35 h
Mobile phone immunity (IEC 60118-13:2016, ANSI C63.19:2011)		IRIL: -25/-28/-10 dB SPL	U-rating: M4

*Battery life in real-life situations depends among other things on the hearing aid features used and streaming time.

Do not modify this equipment without authorization of the manufacturer. Spare parts and instructions for correct repair can be acquired from Widex.